








ECOFLOW

Portable Power Stations for SKYFUZE® Balloon Light Kits

						
Model		RIVER 2 Max	RIVER 2 Pro	DELTA 2	DELTA 2 Extra Battery	DELTA Pro
	Watt Hours (Wh)	512	768	1024	1024	3600
SKYFUZE® 60W	Run Time (Hours)	7.9	11.8	15.8	15.8	55.4
SKYFUZE® 150W		3.3	5.0	6.6	6.6	23.2
	Weight (lbs)	13	17	27	27	99
	Dimensions (inches) L x W x H	10.6" x 10.2" x 7.7"	10.6" x 10.2" x 8.9"	15.7" x 8.3" x 11.1"	15.7" x 8.3" x 11.1"	25" x 11.2" x 16.4"
	Warranty	5 Years	5 Years	5 Years	5 Years	5 Years
	Bluetooth Mobile App	✓	✓	✓	✓	✓
OUTPUT	AC Output Ports	4 outlets, 500W total	4 outlets, 800W total	6 outlets, 1800W total	N/A	5 outlets, 3600W total
	Max Device(s) Power Supported by X-Boost	1000W	1600W	2200W		4500W 7200W
	USB-A Output Max per Port	3 ports, 5V, 2.4A, 12W	3 ports, 5V, 2.4A, 12W	2 ports, 5V, 2.4A, 12W		2 ports, 5V, 2.4A, 12W
	USB-A Fast Charge Max per Port	N/A	N/A	2 ports, 5V, 2.4A / 9V, 2A / 12V, 1.5A, 18W		2 ports, 5V, 2.4A / 9V, 2A / 12V, 1.5A, 18W
	USB-C Output Max per Port	1 port, 5/9/12/15/20V, 5A, 100W	1 port, 5/9/12/15/20V, 5A, 100W	2 ports, 5/9/12/15/20V, 5A, 100W		2 ports, 5/9/12/15/20V, 5A, 100W
	Car Power Output Max	12.6V, 10A/3A/3A, 126W	12.6V, 10A/3A/3A, 126W	12.6V, 10A, 126W		12.6V, 10A, 126W
	DC5521 Output Max per Port	2 ports, 13.6V, 3A	2 ports, 13.6V, 3A	2 ports, 12.6V, 3A		2 ports, 12.6V, 3A, 38W
INPUT	AC Charging Input W	660W	940W	1200W	1200W	1800W Max, 120V~15A, 3000W Max, 240V~12.5A
	0-80% Minutes	48	48	50	80	90
	0-100% Minutes	60	70	80	130	162
BATTERY	Battery Chemistry	LFP	LFP	LFP	LFP	LFP
	Cycle Life	3000 cycles to 80+% capacity	3000 cycles to 80+% capacity	3000 cycles to 80+% capacity	3000 cycles to 80+% capacity	6,500 cycles to 50% capacity, 3,500 cycles to 80% capacity